

## **PROGRAMMING INSTRUCTIONS REVELATION**

---

### **ADMINISTRATION PROGRAMMING**

From the programming extension systemphone:

1. Do not lift the handset
2. Enter the access code
3. Enter the access PIN The display shows the prompt Dial admin code
4. Enter the required admin code
5. Enter any required data
6. To enter another admin code, step back to the Dial admin code prompt by pressing #. Some features require you to press # more than once
7. To finish programming, press HANDS FREE

### **ADMINISTRATION PROGRAMMING CODES**

#### **FEATURE : ADMIN CODE : DEFAULT SETTING**

Advisory message change pre-programmed text : \*4 :

- 1 Phone
- 2 Return at
- 3 Return by
- 4 Call Back At
- 5 At a Meeting
- 6 At Lunch
- 7 At home
- 8 Call
- 9 Holiday

Access (PIN) : 0 : 111

Call logging info enable/disable : 99 : Disabled

Call waiting tone : 95 : No extensions receive call waiting tone

CDS: Associating names and extensions with CDS numbers : \*8 :  
None

CLIR (ISDN) : 30 : No extensions programmed

COLR (ISDN) : 31 : No extensions programmed

3.1 Khz ISDN calls : 32 : No extensions programmed

Divert to/from - set/verify/cancel : 90 : No diversion

Divert on busy - set/verify/cancel : 91 : No diversion

Divert on no answer -set/verify/cancel : 92 : No diversion

Extension access to outgoing line : 8 : All

Extension class of service - day service : 6 : 1

Extension class of service - night service : 7 : 1

Extension names : \*3 : Extension numbers

Incoming ringing telephones day service : 1 : Extensions 20 - 25 and  
Central Bell

Incoming ringing telephones night service : 2 : Extensions 20 - 25 and

## Central Bell

Manager/Secretary Programming (Version D or later software only) :

97 : None

Night service - automatic day service time : \*2 : No time programmed

Night service - automatic night service time: \*1 : No time programmed

On Hold Options - (Version D or later software only)

Music/Tone/Silence on Hold : 98 : 1+6 Tone on Hold 2+6, 3+9, 4+12

Music on Hold

Speed dial numbers (system) - add/delete : 5 : -----

Speed dial numbers (system) - class of service override : 96 : No

Extensions

Systemphones which may not be paged : \*9 : All systemphones may be paged System-wide class 5 restriction enable/disable : \*0 :

Disabled

Recording a personalised greeting (Version L or later software) : \*5 : No message recorded

Replaying a personalised greeting : \*6 : No message recorded

Time and date : 4 : 00:00 01-01-95

Voice Module: Lines on which voice module activated by keying 35\* (Version D or later software only) : 94 : All lines except fax detect lines

Voice Module: Ring Time before voice module activation (Version D or later software only) : 93 : 05 seconds

## **TELEPHONE FEATURE CODES**

Feature : Code

Advisory messages : 45 0-9

Alarm call : 75

Baby monitor : 39

Call back Recall : 44

Call back message - lighting the MESSAGE light on a Systemphone Recall : 45

Call waiting tone protection - during a call Recall : 58

Call waiting tone protection - not during a call : 58

Conference Recall : 3

Divert from : 49 XX

Divert on busy : 47 XX

Divert on no answer : 46 XX

Divert to (all) : 48 XX

Do not disturb - set/cancel : 42

Door open : 36

Extensions : 20 - 31

Extension lock programme : 40 XXX

Extension lock/unlock : 41 XXX

Forward recall Recall : 50

Incoming call pick up (all incoming calls) (Version J and L software only) : 8

Incoming call pick up (all incoming calls) (Version D and later software only) : 66

Line access : 9  
Line access 1 - 4 : 51 - 54  
Line access groups 1 - 3 : 71 - 73  
Night service - on/off (extension 20 only) : 78  
Operator/extension : 20 0  
Page - Systemphones : 34  
PA - answer : 74  
Park - park a call Recall : 57  
Park - retrieve a parked call : 57  
Phone pick-up (extension) : 43 XX  
Phone reset : 79  
Redial : 60  
Speed dial - accessing personal numbers : 61 0 - 9  
Speed dial - programming personal numbers : 62 0 - 9  
Speed dial - accessing system numbers (Version J and L software only)  
: 050 - 699  
Speed dial - accessing system numbers (Version D or later software)  
800 - 899  
Voice call : 33

## **CONFIGURATION PROGRAMMING**

From the programming extension systemphone:

1. Do not lift the handset.
2. Enter the access code (76517)
3. The display shows Dial config code
4. Enter the required config code.
5. Enter any required data.
6. To finish programming, press HANDS FREE

## **CONFIGURATION PROGRAMMING CODES**

Feature : Admin code : Default setting  
Equipped exchange lines : 0 : All lines equipped  
Exchange lines equipped in groups accessed by 71, 72 and 73 : 1 : All  
lines in group 1 accessed by 71  
Hold indication - steady or flashing : 2 : Steady (0)  
PABX access digit : 3 : None programmed  
MF/LD signalling on exchange lines : 4 : MF  
Incoming calls only on an exchange line : 50 : All lines connected for  
incoming and outgoing calls  
Disconnection of an extension : 51 : All extensions connected  
Recall timing for unanswered external transferred calls and  
calls placed on hold. : 52 : 30 seconds  
Divert on no answer timing : 53 : 11 seconds  
Tone on hold - enable/disable (Version J and L software only) : 54 :  
Disabled (0)  
Facsimile tone detection -enable/disable : 55 : Disabled  
CDS enable/disable : 56 : Disabled (0)

ISDN2 access programming : 57 : Disabled ( But if IAU fitted then programmed for lines 1 & 2)  
Exchange line dial tone presented to extensions - enable/disable : 58 : Disabled (0)  
Dial tone detect for PBX access code : 59 : On  
PA equipped - enable/disable : 7 : Disabled  
Specify position for system programming after initial set-up : 8 : 20  
Specify if incoming ringing cycle is required : 90 : Not programmed  
Forward recall signal - earth recall or timed break : 91 : Timed Break 80 ms (2)  
Programming DISA : 93 : Disabled  
Entering codes for class of service restriction and exception : 94 : No codes entered  
Displaying and removing codes for class of service restriction and exception : 95 : No codes entered  
Programming a Doorphone : 97 : Not programmed (0)  
Programming the type of Doorphone : 98 : Doorphone with call button (0)

\*\*\*\*\*

System reset : 99 : N/A

\*\*\*\*\*

Voice Module - enable/disable : \*0 : Disabled (0)  
Incoming exchange line call : handling (Systemphones only) : \*3 : Answer by going off-hook (1)  
Allocating MSN/DDI numbers to extensions : \*4 : No numbers are allocated  
ISDN2 Pabx lines : \*6 : Not programmed  
Point to Point or Point to Multipoint : \*7 : Both lines are PMP

---

**Last revised:**